

## MODEL 11050 SERIES

### KEY FEATURES

- Test Parameters: L/C/R/Z/Y/DCR/Q/D/ $\theta$
- Test Frequencies:
  - 75kHz ~ 30MHz (11050-30M)
  - 1kHz ~ 10MHz (11050)
  - 60Hz ~ 5MHz (11050-5M)
- Test Level: 10mV ~ 5V
- Basic Accuracy: 0.1%
- 7ms high speed measurement
- 3 output impedance modes
- Test signal monitoring function
- Compare & bin-sorting function
- Open/short zeroing & load correction functions
- Detached measurement & display unit design
- Standard Handler, RS-232C, USB storage & external bias current control interface
- GPIB or LAN interface (Optional)

## HF LCR METER MODEL 11050 SERIES

The Chroma 11050 Series HF LCR Meter is a precision test instrument designed to accurately measure and evaluate passive components at high speeds. Its measurement capabilities cover the primary and secondary parameters required for testing the inductance, capacitance, resistance, quality factor and loss factor of passive components. The HF LCR Meter has a broad testing frequency range 75kHz~30MHz/1kHz~10 MHz/60Hz~5MHz suitable for analyzing component characteristics under different frequencies. Its 0.1% basic measurement accuracy provides stable and highly reliable results. A fast 7ms measurement speed effectively increases productivity when working in an automated environment.

In addition to the excellent measurement features found in other Chroma LCR Meters, the 11050 Series provides additional useful functions. It has 3 output impedance modes to satisfy demands for measuring and working with other instruments. The versatile digital display can be configured to best fit the current testing resolution; furthermore, the test signal monitoring function displays the voltage and current that is actually carried to the DUT. The timing settings of trigger delay, measure delay and average number of times allow the measurements to transfer seamlessly to an automated test environment providing accurate results within a limited testing time.

The detached design adopted by the Chroma 11050 Series provides several advantages. Since test processing and the display use separate CPUs, the testing speed is increased and shorter test leads are needed when integrated into an automated test environment. Shorter test leads improve the accuracy of high frequency measurements.

Chroma's 11050 Series HF LCR Meter has multiple remote interface options. Handler and RS-232C remote interfaces come standard for software or hardware control of test conditions, measurement triggers, judge test results, and collecting measured data. The standard USB port saves device settings and controls the output of an external DC bias current source. Optional GPIB and Ethernet remote interfaces are available as well for software control.

Due to the design of modern portable electronic communication devices with thin form factors and low power consumption, required frequency testing of power inductors is increasing. The equivalent series resistance of components has become a critical indicator to identify if it is good or bad. The buffer capacitor plays an important role for overall circuit reliability and must function properly under various voltage transient conditions; the equivalent series resistance must remain at a very low level when operated at high frequencies. The Chroma 11050 Series is focused on testing passive components at high frequencies and with enhanced key measurement capabilities during R&D so that it simulates the user's actual application as closely as possible. The increased accuracy of low impedance measurements demonstrates the usefulness of Chroma 11050 Series in high frequency testing applications.

The Chroma 11050 Series HF LCR Meter was designed with many enhancements and key features to make it the best choice to meet the demands of modern component characterization analysis and high speed testing for automated production line or incoming/outgoing inspection applications.




# Chroma

## TEST MODES - BASIC


### LCR Mode



LCR Mode



LIMIT Mode : low / pass / high





BIN Mode : bin1 ~ bin8 / bin out

## TEST MODES - MULTI-POINT

### LCRZ Mode



LCRZ mode is designed for testing frequency-dependent and voltage-dependent parameters. Capacitor and inductors impedance and equivalent series resistance tend to be affected by changes of frequency. And because of dielectric characteristics, a ceramic capacitors capacitance is sensitive to test voltage. By LCRZ mode, it is easy to evaluate these characteristics.



- ☒ Frequency / Level setting: 9 sets
- ☒ Sequence / Step test modes
- ☒ Pass / Fail judgment & count

### Bias Scan Mode

Bias scan mode is designed for testing the saturation characteristic of magnetic components. The inductance and impedance of an inductor drops with the increase of bias current. Integrated with Chroma bias current source, the HF LCR meter can control the current setting and output. Bias scan mode is helpful to program the test process.




- ☒ Frequency / Bias Current setting: 27 sets
- ☒ Sequence / Step test modes
- ☒ Pass / Fail judgment & count

## TEST MODES - ANALYZER

### Parameter Sweep Mode

Parameter sweep mode is designed for plotting various characteristic curves. Up to 401 plotted points make the curve smoother. Users can use reference curve store/recall function to easily compare two curves. If there is a need to check the detailed measurements, just turn on the cursor or switch to table mode.




Parameter Sweep Mode

- ☒ Frequency / Level / Bias Current sweep: 401 points max.
- ☒ Plot / Table modes
- ☒ Reference Curve store / recall




## WIRING INSTRUCTIONS - TEST FIXTURE CONNECTION



## ORDERING INFORMATION

- 11050 : HF LCR Meter, 1kHz~10MHz
- 11050-5M : HF LCR Meter, 60Hz~5MHz
- 11050-30M : HF LCR Meter, 75kHz~30MHz
- A110211 : Test fixture (DIP)
- A110234 : Test leads (1M)
- A110501 : 4-terminal SMD test fixture
- A110502 : Bias current source (0~5A)
- A110503 : Bias current test fixture (10MHz)
- A110504 : Bias current protection box
- A110505 : Bias current source (5A~20A)
- A133509 : GPIB & Handler interface
- A133510 : LAN & USB-H interface
- B110500 : Extension test lead for automation (BNC to SMA, 1M)


## PANEL DESCRIPTIONS



- |                           |                            |
|---------------------------|----------------------------|
| 1. LCD Panel              | 5. Measurement Terminals   |
| 2. Buttons                | 6. Power Switch            |
| 3. Remote Control Port    | 7. Panel Bracket           |
| 4. Power & Test Indicator | 8. Optional Interface Slot |


- |                         |                                    |
|-------------------------|------------------------------------|
| 9. Remote Control Port  | 13. Ext. Bias Current Control Port |
| 10. RS-232C & USB Ports | 14. Remote Control Port            |
| 11. Power Inlet         | 15. Handler Interface              |
| 12. Grounding Terminal  | 16. Ext. Voltage Terminal          |

Bias current source (0~5A)  
A110502




1. Power Switch
2. Indicator: POWER \ BIAS and ERROR indicators
3. Current Output End: BIAS Drive+ & Drive- end
4. InterLock: It is mainly used for the fixture with protection device while coordinating with A110503 Bias Current test fixture. It can disable Interloc function via standard accessory InterLock short-circuited component while coordinating with A110504 Bias Current protection box.

Bias Current Source (5A~20A)  
A110505




1. Power Switch
2. Indicator: POWER \ BIAS and ERROR indicators
3. InterLock: It is for the fixture with a protective device such as the A110503 Bias Current Test Fixture. When the A110504 Bias Current Protection Box is used, the Interlock short circuit fixture on the A110505 will turn off the Interlock function.
4. Current Output Terminal (Drive+ & Drive-)
5. DUT DCV Detect Terminal (+VSense-)
6. DUT Voltage Monitor Terminal (V-Monitor)
7. Air Inlet

Bias Current Test Fixture  
A110503



1. Thimble: It is for pressing DUT on the test platform.
2. Clamping: Press the clamp down once the DUT is put then the thimble pressed the DUT.

Bias Current Protection Box  
A110504



1. LCR Meter UNKNOWN Connection Terminal: It is for connecting UNKNOWN terminal of 11050 HCUR, HPOT, LPOT and LCUR.
2. DUT UNKNOWN Connection Terminal: It is for connecting UNKNOWN terminal of DUT HCUR, HPOT, LPOT and LCUR.




## SPECIFICATIONS

|                           |   |  |  |
|---------------------------|---|--|--|
| Model                     | 11050-30M   | 11050  | 11050-5M                                     |
| Test Parameter            | L, C, R, Z, Y, Q, D, $\theta$   |  | L, C, R, Z, Y, DCR, Q, D, $\theta$           |
| Test Signal               |   |  |  |
| Test Frequency            | 75kHz ~ 30MHz<br>$\pm (0.1\% + 0.01\text{Hz})$  | 1kHz ~ 10MHz<br>$\pm (0.1\% + 0.01\text{Hz})$  | 60Hz ~ 5MHz<br>$\pm (0.1\% + 0.01\text{Hz})$ |
| Test Level                | 10mV ~ 1V ; $\pm [(10 + \text{fm})\% + 10\text{mV}]$<br>fm: test frequency [MHz]          | $\leq 1\text{MHz} : 10\text{mV} \sim 5\text{V} ; \pm [(10 + \text{fm})\% + 1\text{mV}]$<br>>1MHz : 10mV ~ 1V ; $\pm [(10 + \text{fm})\% + 1\text{mV}]$<br>fm: test frequency [MHz] |  |
| Output Impedance          | 100 $\Omega$ , 25 $\Omega$  | 100 $\Omega$ , 25 $\Omega$ , OFF   |  |
| Measurement Display Range |   |  |  |
| L                         | 0.00001uH ~ 99.999MH  |  |  |
| C                         | 0.00001pF ~ 999.999F  |  |  |
| R, Z                      | 0.01m $\Omega$ ~ 9999.99M $\Omega$  |  |  |
| DCR                       | --  | 0.01m $\Omega$ ~ 999.99M $\Omega$  |  |
| Q, D                      | 0.00001 ~ 99999   |  |  |
| $\theta$                  | -90.00° ~ 90.00°  |  |  |
| Basic Accuracy            |   |  |  |
| Z                         | $\pm 1.5\%$   | $\pm 0.1\%$  |  |
| $\theta$                  | $\pm 0.3^\circ$   | $\pm 0.04^\circ$   |  |
| DCR                       | --  | $\pm 0.1\%$  |  |
| Measurement Speed         | Very Fast : 7ms, Fast : 15ms, Medium : 150ms, Slow : 295ms                                |  |  |
| Communication Interface   | RS-232C, Handler, USB storage, External bias current control, GPIB (option), LAN (option) |  |  |
| Measurement Functions     |   |  |  |
| Trigger Mode              | Internal, Manual, External, Bus   |  |  |
| Range Switching Mode      | Auto, Hold  |  |  |
| Equivalent Circuit Mode   | Series, Parallel  |  |  |
| Judgment                  | Compare, Bin-sorting  |  |  |
| Correction                | Open/Short Zeroing, Load Correction   |  |  |
| Others                    |   |  |  |
| Operating Environment     | Temperature : 0°C ~ 40°C ; Humidity : 10% ~ 90%   |  |  |
| Power Consumption         | 60VA max.   |  |  |
| Power Requirement         | 100 ~ 240V $\pm 10\%$ , 47Hz ~ 63Hz   |  |  |
| Dimension (H x W x D)     | 230 x 428 x 290 mm / 9.06 x 16.85 x 11.42 inch  |  |  |
| Weight                    | Approx. 8 kg / 17.64 lb   |  |  |

Get more product and global distributor information in Chroma ATE APP



iOS



Android

Search Keyword

11050

HEADQUARTERS  
CHROMA ATE INC.  
88 Wenmao Rd.,  
Guishan Dist.,  
Taoyuan City  
333001, Taiwan  
T +886-3-327-9999  
F +886-3-327-8898  
www.chromaate.com  
info@chromaate.com

U.S.A.  
CHROMA SYSTEMS  
SOLUTIONS, INC.  
19772 Pauling,  
Foothill Ranch,  
CA 92610  
T +1-949-600-6400  
F +1-949-600-6401  
www.chromausa.com  
sales@chromausa.com

EUROPE  
CHROMA ATE EUROPE B.V.  
Morsestraat 32, 6716 AH  
Ede, The Netherlands  
T +31-318-648282  
F +31-318-648288  
www.chroma.eu.com  
salesnl@chroma.eu.com  
  
CHROMA GERMANY GMBH  
Südtiroler Str. 9, 86165,  
Augsburg, Germany  
T +49-821-790967-0  
F +49-821-790967-600  
www.chroma.eu.com  
salesde@chroma.eu.com

JAPAN  
CHROMA JAPAN  
CORP.  
888 Nippa-cho,  
Kouhoku-ku,  
Yokohama-shi,  
Kanagawa,  
223-0057 Japan  
T +81-45-542-1118  
F +81-45-542-1080  
www.chroma.co.jp  
info@chroma.co.jp

KOREA  
CHROMA ATE  
KOREA BRANCH  
3F Richtogether  
Center, 14,  
Pangyoeyeok-ro 192,  
Bundang-gu,  
Seongnam-si,  
Gyeonggi-do  
13524, Korea  
T +82-31-781-1025  
F +82-31-8017-6614  
www.chromaate.co.kr  
info@chromaate.com

CHINA  
CHROMA ELECTRONICS  
(SHENZHEN) CO., LTD.  
8F, No.4, Nanyou Tian  
An Industrial Estate,  
Shenzhen, China  
T +86-755-2664-4598  
F +86-755-2641-9620  
www.chroma.com.cn  
info@chromaate.com

SOUTHEAST ASIA  
QUANTEL PTE LTD.  
(A company of Chroma Group)  
25 Kallang Avenue #05-02  
Singapore 339416  
T +65-6745-3200  
F +65-6745-9764  
www.quantel-global.com  
sales@quantel-global.com